

Completely pre-assembled Signal Towers / ClearSIGN

ClearSIGN BM Contin. tone 24VDC MC



Part No.:	656.100.03
Series:	ClearSIGN

MECHANICAL DATA				
Height	320 mm			
Diameter	85 mm			
Materials	PC PC/ABS			
Dome colour	Clear			
Housing colour	White			
Protection category	IP66			
Connection	IO-LINK M12 plug 4-pole Push-in terminal			
cross-sectional area minimum	0,14mm ² / 26AWG			
cross-sectional area maximum	0,50mm ² / 20AWG			
Cable entry	Membrane grommet			
Cable entry minimum	d = 1 mm			
Cable entry maximum	d = 9 mm			
Tension relief	Present (conforms to VDE)			
Type of fixing	Base mounting			
Working temperature minimum	-20°C			
Working temperature maximum	+50°C			
Weight with packaging	493 g			
Product weight	327 g			

ELECTRICAL DATA			
Operating voltage	24V		
Operating voltage type	DC		
Operating voltage tolerance	+/- 10%		
Rated operational voltage	24 VDC		
Rated operational current	420 mA		
Rated inrush current	500 mA		
Protection class	Protection class 2		
Pollution degree	3		
connectivity	IO-Link		

OPTICAL DATA		
Light source	LED	
Light colour	MC >1.000.000 colours	
Optical signal image	Permanent	
Service life optical	50,000 h maximum	

ACUSTICAL DATA

For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.




Completely pre-assembled Signal Towers / ClearSIGN

ClearSIGN BM Contin. tone 24VDC MC

Volume (max) at 1m distance	85,0 dB (A)
Acoustic signal image	Continuous tone
Audio frequency	4400 Hz
Acoustic service life	5,000 h minimum

APPROVAL DATA		
Conforms with CE	Yes	
WEEE	Yes	
Conforms with RED directive	No	
Conform with ATEX-directive	No	
Conforms with CCC	No	
Conforms with UL	No	
Conforms with FCC	No	
Conforms with IC	No	
EAC certificate available	Yes	
Conforms with AS-I	No	
ICAO Certification	No	
Conforms with GL	No	
Conforms with RoHS CN	No	
Conforms with VdS	No	

DRAWING



For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.